



Amendments to the Claims

This listing of claims will replace all prior versions and listings of claims in the application.

1. (Currently Amended) A programmable gain attenuator comprising:
 - a termination resistor;
 - a first termination switch connecting one side of the termination resistor to a first output;
 - a second termination switch connecting another side of the termination resistor to a second output;
 - a first resistor ladder arranged between a first input and the first side of the termination resistor;
 - a first plurality of switches each connecting a corresponding tap from the first resistor ladder to the first output, wherein the first plurality of switches are connected in a first matrix having two or more rows and two or more columns, wherein the switches in each particular column of the first matrix are arranged in parallel with the other switches in the particular column, having their respective inputs directly coupled together, and their respective outputs directly coupled together;
 - a second resistor ladder arranged between a second input and the second side of the termination resistor; and

a second plurality of switches each connecting a corresponding tap from the second resistor ladder to the second output, wherein the second plurality of switches are connected in a second matrix having two or more rows and two or more columns, wherein the switches in each particular column of the second matrix are arranged in parallel with the other switches in the particular column, having their respective inputs directly coupled together, and their respective outputs directly coupled together,

wherein some of the switches of the first plurality of switches are turned on for interpolation, and

wherein some of the switches of the second plurality of switches are turned on for interpolation.

2. (Original) The programmable gain attenuator of claim 1, wherein the first and second matrices each includes a fine matrix and a coarse matrix, which are controlled using fine and coarse selection logic, respectively, through a multiplexer.

3. (Original) The programmable gain attenuator of claim 1, wherein the switches in each of the first and second matrices are controlled so as to form corresponding submatrices with some of the switches in each submatrix on, and other switches off.

4. (Original) The programmable gain attenuator of claim 1, further including a plurality of resistors connected between the corresponding taps of the first and second resistor ladders.

5. (Currently Amended) A single-ended programmable gain attenuator comprising:

a termination resistor;
a termination switch connecting one side of the termination resistor to an output;
a resistor ladder arranged between an input and the one side of the termination resistor; and
a plurality of switches each connecting a corresponding tap from the resistor ladder to the output,

wherein the switches are connected in a matrix having two or more rows and two or more columns, wherein the switches in each particular column of the matrix are arranged in parallel with the other switches in the particular column, having their respective inputs directly coupled together, and their respective outputs directly coupled together, and

wherein some of the switches of the first plurality of switches are turned on for interpolation.

6. (Original) The programmable gain attenuator of claim 5, wherein the matrix includes a fine matrix and a coarse matrix, which are controlled using fine and coarse selection logic, respectively, through a multiplexer.

7. (Original) The programmable gain attenuator of claim 5, wherein the switches are controlled so as to form a submatrix with some of the switches in the submatrix on, and other switches off.

8. (Canceled)

9. (Currently Amended) A single-ended programmable gain attenuator comprising:

a resistive ladder;

a plurality of switches corresponding to the resistive ladder and connected in a matrix to interpolate a desired voltage at the output, and connected to corresponding taps of the resistive ladder and to an output, said plurality of switches arranged in two or more rows and two or more columns, wherein the switches in each particular column of the matrix are arranged in parallel with the other switches in the particular column, having their respective inputs directly coupled together, and their respective outputs directly coupled together; and

a termination resistor.

10. (Currently Amended) A single-ended programmable gain attenuator comprising:

a resistive ladder;

a plurality of switches corresponding to the resistive ladder and connected to interpolate a desired voltage at the output, and connected to corresponding taps of the resistive ladders and to an output;

a termination resistor;

a fine selection logic for selection fine control switches out of the plurality of switches;

a coarse selection logic for selection fine control switches out of the plurality of switches; and

a multiplexer for passing control signals from the fine and coarse selection logic to the plurality of switches,

wherein the switches are arranged in a matrix having two or more rows and two or more columns, wherein the switches in each particular column of the matrix are arranged in parallel with the other switches in the particular column, having their respective inputs directly coupled together, and their respective outputs directly coupled together.

11. (Canceled)

12. (Canceled)